

WAVEGUIDE BANDPASS FILTER

Part Number:- WG 132 F1V1  
 to the following specification:- WG 132 - S1  
 Issued:- 12/10/2017

Centre Frequency (fo)	28 GHz
Bandwidth	2 GHz
Insertion Loss fo ± 1 GHz	1.0 dB Max
Return Loss fo ± 1 GHz	15 dB Min
Rejection	
DC - (fo - 2 GHz)	25 dB Min
(fo + 2 GHz) - 40 GHz	25 dB Min
Dimensions excluding connectors	55 x 15 x 10 mm Typical
Connectors	k Type Female
Operating Temperature Range	0 to +50°C
External Finish	Matt Black
Notes :	



